



UNIT DISCONTINUED:

2650 Sept. 21, 1994

Page 1 of 2

ITEM NO.	PART NO.	DESCRIPTION	QTY
1	450076-31	Armature & Fan(9 Teeth)	1
2	464277-00	Field (Incl. 31)	1
3	143803-00	Brush	2
4	445860-00	Brush Spring	2
5	449899-05	Brush Ring (Incl. 4)	1
7	450563-00	Switch (On/Off)(2650 only)	1
	450270-00	Switch (Variable Speed) (2660 only)	1
8	330072-98	Cord & Plug (18-2 SJ)	1
φ9	330003-04	Ball Bearing	1
φ10	330003-04	Ball Bearing	1
11	150196-00	Switch (Rev.)	1
φ12	400166-00	Terminal	2
13	330005-01	Cord Protector	1
14	450367-00	Belt Clip	1
15	445217-02	Sleeve	1
16	447866-00	Fan Baffle	1
φ17	464231-00	Field Case	1
18	450594-00	Handle Cover	1
19	450747-00	Gear Case Cover (Incl. 10,32)	1
20	450743-02	Gear Case (Incl. 33,34)	1
22	330019-18	M4 x 38 Thread Forming Screw	2
23	450741-00	Spindle & Gear (49 Teeth)	1
24	86964-00	8-16 x 13/16" Thread Forming Screw	3
25	233304-00	Blank Nameplate (2650)	1
	152165-08	Nameplate (2660)	1
26	449192-00	Terminal	4
27	89210-00	Retaining Ring	2
28	86211-00	Spring	1
φ29	96558-00	Clutch (Incl. 27)	2

ITEM NO.	PART NO.	DESCRIPTION	QTY
30	448859-05	Clutch Housing (Incl. 37,60)	1
31	448269-00	6-19 x 2 1/4" Thread Forming Screw	2
32	131557-00	Sleeve Bearing	1
φ33	330003-09	Ball Bearing	1
34	149718-00	8-16 x 3/8" Thread Forming Screw	2
φ37	450907-00	Bearing	1
38	21287-00	Guide	1
39	448754-01	Locator	1
41	96540-01	Spindle (Incl. 42,55) (1/4" Hex)	1
42	696631-00	Ball (9/64)	1
φ43	341623-00	Bit Holder	1
44	364066-00	Bit	1
45	450769-00	Collar	1
47	448865-00	Cap	1
49	450750-00	Retaining Ring	1
φ50	696534-00	Lip Seal	1
φ51	450228-00	J-Strip (Brush Terminal)	2
55	94518-00	Ball Retainer	1
56	450966-00	Gasket	1
φ58	449890-00	Dust Seal	1
59	450147-01	Nosepiece (Incl. 39,45,47, 50,58)	1
φ60	696534-00	Seal	1

NO LOAD TEST SPECIFICATIONS:

AMPS		SPEED	
MIN.	MAX	MIN.	MAX.
2.1	2.65	5200	5900

EXTRA EQUIPMENT:

(Not Supplied With Unit)

450773-00	Connection Diagram (Lucerne with short brush leads)
381188-00	Connection Diagram (Capax)
682245-00	Connection Diagram(Lucerne)
69542-00	1 lb. can clutch grease
761995-00	Polyrex Grease (6 oz.)
283484-00	Polyrex Grease (32 oz.)

IMPORTANT! To assure product SAFETY and RELIABILITY, repairs, maintenance and adjustment should be performed by BLACK & DECKER Service Centers or other qualified service organizations, always using BLACK & DECKER replacement parts.

When servicing Double Insulated Tools, it is extremely important that ONLY IDENTICAL REPLACEMENT PARTS BE USED and that REASSEMBLY OF TOOL IS IDENTICAL TO THE ORIGINAL ASSEMBLY.

DRYWALL SCREWDRIVER

Cat. no.	Type	Volts	Amps	RPM
2650	100	120	4.5	4000
2660	100	120	4.5	0-4000
AC Only				

Black & Decker (U.S.), Inc.
Product Service Division
Hampstead, Maryland 21074

COPYRIGHT© 2005. All Rights Reserved.

Parts list, pricing, and availability subject to change. Please visit www.dewaltservicenet.com for current parts information.