# Milwankee

#### **SERVICE PARTS LIST**

## BULLETIN NO. 54-00-2718


 SPECIFY CATALOG NO. AND SERIAL NO. WHEN ORDERING PARTS

 M18™ FUEL™ 1-3/4" SDS-Max Rotary Hammer with One-Key

 CATALOG NO.
 2718-20

 SERIAL NUMBER
 J97A & J97B

REVISED BULLETIN DATE Apr. 2022
WIRING INSTRUCTION



Service for the ELECTRONICS on Milwaukee Tool ONE KEY Products can only be performed at this Milwaukee factory Central Repair Center:

MILWAUKEE TOOL Central Repair 1401 Sycamore Avenue • Greenwood, MS 38930-7277

Please send your tool directly to this location for service.

Or

Via e-Service at: www.milwaukeetool.com/e-service questions, please call 1.800.SAWDUST (1.800.729.3878)

)r

Return it to a MILWAUKEE *factory* Service Center location, freight prepaid and insured. A copy of the proof of purchase should be included with the return product.

If you have questions please contact Milwaukee Product Service at:

Product Technical Support via phone at: 262.783.8642

Or

Via email at: METProductSupport @milwaukeetool.com

#### SERVICE PARTS LIST


Milwankee SPECIFY CATALOG NO. AND SERIAL NO. WHEN ORDERING PARTS

M18™ FUEL™ 1-3/4" SDS-Max Rotary Hammer with One-Key™ STARTING SERIAL 2718-20 **J97A & J97B** CATALOG NO.

REVISED BULLETIN

DATE Apr. 2022

WIRING INSTRUCTION SEE PAGE 4



42

48a


48 48b 48c 48d 62


FIG.	PART NO.	DESCRIPTION OF PART	NO. REQ.
21	42-62-0013	Side Handle Assembly	(1)
21a	05-89-0015	Fixing Screw	(1)
21b	45-88-0103	Flat Washer	(1)
21c	43-72-0002	Holder 1	(1)
21d	43-72-0003	Holder 2	(1)
21e	06-55-0018	Hex Nut	(1)
21f	31-05-0011	Clamping Ring	(1)
21g	44-66-0049	Support Plate	(1)
21h	44-90-0046	Ring	(1)
21j	43-76-0012	Absorber Housing	(2)
21k	44-52-0013	Absorber	(1)
21m	43-87-0015	Bellows	(1)
21n	43-24-0010	Extension	(1)
		Side Handle Cap	(1)
21q	43-98-5316	Side Handle	(1)
<b>★</b> 22	14-29-0014	Gearcase Assembly	(1)
22e		Flat Washer	(1)
22f		M6 x 10mm BUH Hex Recess Screw	(1)
39h	06-82-0032	M4 x 12mm Pan Hd. ST T-20 Screw	(1)
41	44-50-0013	Lock Cam	(1)
	34-40-5308		(1)
43	34-40-0088	O-Ring	(1)
44	42-70-0028	EM-Clutch Assembly	(1)
45	16-01-0010	Rotor Assembly	(1)
46		Electronics Assembly	(1)
46f	44-52-0066	Foam Pad (Set of two)	(1)
	05-88-0028	M6 x 55mm Pan Hd. Taptite T-30 Screw	(4)
48	31-44-0118	Housing Assembly	(1)

62

<b>FIG</b> . 48a	PART NO.	DESCRIPTION OF PART Housing Halve Cover	NO. REQ. (1)
48b		Housing Halve Support	(1)
48c	06-82-2025	M3.5 x 16mm Pan Hd. Plastite T-10 Scre	
48d	05-78-5311	M5 x 18mm Pan Hd. ST T-20 Screw	(ÌŚ)
49	43-62-0038	Handle Kit	`(1) <sup>′</sup>
49a		Handle Support	(1)
49b		Handle Cover	(1)
49c	44-66-0057	Auto Stop Plate	(1)
49d	44-06-0014	Bluetooth Indicator Lens	(1)
49e	44-06-0018	Bluetooth Working Lens	(1)
49f	42-42-0054	Foam Bushing	(3)
50	31-21-0066	Coin Cell Cover Kit	(1)
50a		Coin Cell Cover	(1)
50b	05-81-1100	M2.6 x 6mm ST Phillips Screw	(2)
51	23-66-5027	On-Off Switch	(1)
52	45-72-0012	Switch Trigger	(1)
53	40-50-0059	Spring	(1)
54	40-50-0027	Spring Plate	(1)
55	44-60-0089	Lock Button	(1)
57		3V Coin Cell Battery (CR2032H)	(1)
62	12-20-0138	Service Nameplate	(1)

- See page 2 for the exploded view and parts listing of the mechanical portion of the tool and service fixtures.
- See page 3 for lubrication instructions, torques chart, maintenance instructions and service kits.
- See Page 4 for wiring instructions.





#### • 14-46-2718 MAINTENANCE SERVICE KIT


THIS KIT CONTAINS:					
$\overline{}_1$	45-12-5316	Rubber Dust Shield			
1	34-60-5316	Retaining Ring			
2	34-40-5316	Spindle O-Ring			
2	34-60-5319	O-Ring			
2	45-06-5317	Turcon Seal			
2	34-40-5308	O-Ring			
2	42-42-0054	Foam Bushing			
1	14-46-0099	Bearing Shield Assembly			
1	34-60-0072	Back Press Ring			
2	34-60-0078	O-Ring			
1	43-44-0012	Rubber Gasket			
1	34-40-5309	O-Ring			
1	44-90-5319	Spring Ring			
3	49-08-5355	'Q2' Grease (2.8oz/80g tube)			

FASTENER TORQUE SPECIFICATIONS (IN./LBS.)							
		SEATING TORQUE					
FIG. NO.	WHERE USED	in/lbs	kgf/cm	Nm			
34	Selector Bracket Clamp Plate	11	13	1.3			
38	Gearcase Cover	44±3	51±4	5.0			
47	Motor Housing	56	65	6.4			
48d	Housing Halve Cover	25	29	2.9			
48c	Housing Halve Cover	11	13	1.3			
50b	Coin Cell Cover	2.6	3.05	0.3			
39h	Selector Knob	16	18	1.8			
39h	On-Off Switch	11	13	1.3			
	Switch Termination Screws	8	10	1.0			
	Ground Screw-Gearcase	44	50	5.0			

### **ELECTRICAL SPECIFICATIONS**

#### **Handle and Base Cutaway**

Model 2718-20 Cordless Rotary Hammer shown



AVOID PINCHED WIRES, BE SURE THAT ALL WIRES AND SLEEVES ARE PRESSED COMPLETELY DOWN IN WIRE GUIDES AND TRAPS.

PRIOR TO INSTALLING THE HANDLE COVER ONTO THE HANDLE SUPPORT, BE SURE THAT THERE ARE NO INTERFERENCES.